Smart Node
Discover the Joy of Smart Living

smartnode.in

SCENE CONTROLLER

With Touch Interfaces and with Keypad

Smart Node
Discover the Joy of Smart Living

PANEL

SCENE CONTROLLER

WHAT IS IN THE BOX?

WITH PANEL

Scene controller

Touch Interface

Touch cable

SD.SSC.1 TECHNICAL INFORMATION

Operating Voltages	100 - 240 VAC
Module size	2M
Operating temperature	0°C - 65°C Non condense
Warranty	5 years
Shock proof	Yes
Water resistance	No
Dimension	92.60mm X 89.10mm

TECHNICAL ATTRIBUTES TI.4S

Scene Controller

Module size	2M
TI dimension	92.60mm X 89mm
TI shock proof	Yes
TI water resistance	Yes
Contact type	Capacitive
Mounting type	Wall mount
Touch button	4
Remote control working range	8 meter
Wireless type	Wi-Fi 2.4 GHz 802.11 b/g/n

TECHNICAL ATTRIBUTES TI.8S

Scene Controller

Module size	6M
TI dimension	226.20mm X 89mm
TI shock proof	Yes
TI water resistance	Yes
Contact type	Capacitive
Switch type	IR switch
Mounting type	Wall mount
Touch button	8
Remote control working range	8 meter
Wireless type	Wi-Fi 2.4 GHz 802.11 b/g/n

8 SCENE CONTROLLER TOUCH

16 scenes in 8 switches with tap and long press options

4 SCENE CONTROLLER TOUCH

8 scenes in 4 switches with tap and long press options

TUTORIALS

TAP ON THE BUTTONS

To start configuration mode in Scene Controller

To add a Scene controller to the Smart Node mobile app

DIAGRAMS

Smart Node
Discover the Joy of Smart Living

KEYPAD

SCENE CONTROLLER

WHAT IS IN THE BOX?

WITH KEYPAD

Scene controller

Keypad

Touch cable

SD.SSC.1 TECHNICAL INFORMATION

Operating Voltages	100 - 240 VAC
Module size	2M
Operating temperature	0°C - 65°C Non condense
Warranty	5 years
Shock proof	Yes
Water resistance	No
Dimension	92.60mm X 89mm
Touch button / Keypad	4 or 8
Operating Voltages	24 VDC
Power consumption per LEDs	10mA

COLOR CODE

Color Cable	Input (Switch)	Output (LED)
Red	Vcc	Vcc
Black	Ground	Ground
Blue	I1	01
White	I2	02
Green	I3	03
Brown	I4	04
Purple	I5	05
Orange	I6	06
Grey	I7	07
Yellow	I8	08

16 scenes in 8 switches
with tap and long press options

TUTORIALS

TAP ON THE BUTTONS

To start configuration mode in Scene Controller

To add a Scene controller to the Smart Node mobile app

DIAGRAMS

24V
G
D1
D2
D3
D4
D5
D6
D7
D8
24V
G
K1
K2
K3
K4
K5
K6
K7
K8
D-COM
K-COM
D1
K1
D2
K2
D3
K3
D4
K4
D5
K5
D6
K6
D-W
→