



HOME LINK PRO

8" Screen with Knob

SI.HP



Quick Links

[Product Overview](#)

[Product Features](#)

[Technical Specification](#)

[Installation](#)

Product Description

Product Overview :-

Model Number: SI. HP

Description:

Home Link Pro is a smart home control panel with an 8-inch touchscreen and a control knob, offering seamless access to all automation features, including load control, dimming, scene execution, etc.

Application:

It is ideal for residential homes, hotels, offices, and commercial spaces, providing centralized management of lighting, dimming, scenes, and other smart devices.

Product Features :-

- Manage all loads connected with SmartNode devices, including lights, curtain, AC, etc. directly from the Home Link Pro.
- Configure and customize smart home scenes from SmartNode application.
- Enhances navigation and quick adjustments with knob.
- Single & Double Dots Switches used to execute predefined scenes or control individual switches.
- Proximity sensor enables fast response by detecting nearby objects or motion.
- Screensaver activates automatically after a set period of inactivity.
- Only one user ID can be assigned per Home Link Pro for secure and personalized control.

Product Benefits :-

- Activate scene modes with one touch on the screen panel, making it easy to switch between different settings like "Night," "Morning," "Vacation," and "Movie."
- Provides an intuitive and user-friendly interface.
- No need for an application to operate load.
- Centralized control for a seamless smart automation experience.

Technical Details

Technical Specification:-

Operating Input Voltage	100VAC - 240VAC
Supported Frequency	50-60 Hz
RAM	2GB
ROM	16GB
Screen size	6 inch
Port	USB Type-C Port
OS	Android 11
Color	Black
Dimensions	238.4mm x 125mm x 36.4mm (With the back base)
Working Temperature	0°C to +40°C non condense
Working Humidity	5% to 90%RH (Non-condensing)
Communication Protocol	Wi-Fi 2.4 GHz 802.11 b/g/n
Warranty	5 years

Installation

- Turn off the main power and confirm the live wire is inactive using a test pencil.
- Separate the back base from the screen panel using the built-in magnetic force.
- Connect the live wire to terminal L and the neutral wire to terminal N.
- Fasten the base to the wall box with mounting screws.
- Fix the Home Link Pro back to the base using the built-in magnetic force.

Note: Avoid overtightening screws to prevent screen or hardware damage. If the panel is not flat after installation, do not press the screen forcefully; check the wall box and base installation instead.

Safety Information:-

- This product must be installed by professional electricians.
- DO NOT install with power applied to the device.
- DO NOT expose the device to moisture.
- Verify input voltage compatibility with the device.
- Secure and label wiring for easy maintenance.

User Interface and Ports:-

