



Installation Instructions


(For Scene Controller)

What is in the box?

Smart Device



Touch Panel



Cable



S.4 / S.8

Technical specifications

| Technical Attributes | |
|-------------------------------------|-------------------------|
| Module size | 2M |
| Mode of operation | Touch, IR remote |
| Color | Black and white |
| Product (module) dimensions (in mm) | 52mm x 40mm x 20mm |
| Product (module) weight | 40gms |
| Operating voltages | 100-240 VAC. |
| Operating temperature | 0°C - 65°C non condense |
| Shock proof | Yes |
| Water resistance | No |
| Warranty | 5 Years |

TS.4/TPS.4

Technical specifications

| Technical Attributes | |
|-------------------------------|----------------------------|
| Module size (touch switch) | 2M |
| Touch switch dimension | 45mm x 45mm x 20mm |
| Touch switch shock proof | Yes |
| Touch switch water resistance | Yes |
| Contact type | Capacitive |
| Switch type | IR switch |
| Mounting type | Wall mount |
| Button touch switch | 4 |
| Remote control working range | 8 meter |
| Wireless type | Wi-Fi 2.4 GHz 802.11 b/g/n |
| App support | Android / iOS |
| Controller type | Third party application |
| Warranty | 5 Years |
| Weight | 26 gms |

TS.8/TPS.8


Technical specifications

| Technical Attributes | |
|------------------------------|----------------------------|
| Module size | 6 M |
| Touch panel dimension | 240mm x 95mm x 10mm |
| Touch panel shockproof | Yes |
| Touch panel water resistance | Yes |
| Contact type | Capacitive |
| Switch type | IR switch |
| Mounting type | Wall mount |
| Button touch switch | 8 |
| Remote control working range | 8 meter |
| Wireless type | Wi-Fi 2.4 GHz 802.11 b/g/n |
| App support | Android / iOS |
| Controller type | Third party application |
| Warranty | 5 Years |

8 Scene Controller Touch



4 Scene Controller Touch



- ▶ 8 scenes in 4 switches /16 scenes in 8 switches with tap and long press options.

To start the configuration mode in Scene controller

<https://youtu.be/B1FenRfHGRY>

To add a Scene controller to the Smart Node mobile application

<https://youtu.be/MrtEtQ3w1Ng>